

*B016 PLUG MODIFICATION HELPS PREVENT MIS-MATING BUT IS NOT REQUIRED

CONNECTOR (KEY)	CONNECTOR RECEPTACLE	CONNECTOR MATING PLUG	
A	DT04-12PA-B016	DT06-12SA-B016 *	
В	DT04-12PB-B016	DT06-12SB-B016 *	
С	DT04-12PC-B016	DT06-12SC-B016 *	
D	DT04-12PD-B016	DT06-12SD-B016 *	

5A FOR BRIEF PERIODS ALLOWED ON EACH OUTPUT PAIR (NOT TO EXCEED MAX UNIT CURRENT). SEE

EACH OUTPUT HAS SHORT CIRCUIT/OVERLOAD/OPEN LOAD DETECTION AND PROTECTION.

SOLID ILLUMINATED OUTPUT LED = ON, EXTINGUISED OUTPUT LED= OFF, OUTPUT LED FLASHING AT 2HZ

CAN LED FLASHING AT 0.5HZ = COMMUNICATION OK, CAN LED FLASHING AT 2HZ = UNIT OVER TEMPERATURE, CAN LED 0.5S ON/4.5S OFF = NO COMMUNICATION. EXTINGUISHED CAN LED = MICRO

POWER LED ILLUMINATED = POWERED, EXTINGUISHED POWER LED = NO POWER CAN BAUD RATE IS SOFTWARE CONFIGURABLE (125KBPS, 250 KBPS, 500KBPS, 1MBPS).

	-			
INPUT 4:	INPUT 3:	INPUT 2:	INPUT 1:	lsb of Can ID:
0	0	0	0	0
0	0	0	1	1
0	0	1	0	2
0	0	1	1	3
0	1	0	0	4
0	1	0	1	5
0	1	1	0	6
0	1	1	1	7
1	0	0	0	8
1	0	0	1	9
1	0	1	0	А
1	0	1	1	В
1	1	0	0	С
1	1	0	1	D
1	1	1	0	E
1	1	1	1	F